
# **FUMECUBE LITE**







## **Description & features**

- Run LED & speed control
- Highest grade HEPA and carbon technology
- Adjustable airflow
- **Quiet in operation**
- Simple to install and easy to relocate

#### **Filters**



Main Filter Code

110507

Description

**HEPA/Chemical** 



Pre-Filter Code

200036

Description

F5 Pad

### **Specification**

Voltage	230v
Single Arm Part Number	072082
Dual Arm Part Number	072083
Wattage	0.32kW
Frequency	50Hz / 60Hz
Cabinet Height	346mm
Cabinet Width	286mm
Cabinet Depth	291mm
Cabinet Weight	12kg
Airflow	170m3/h
Sound Level	<60dBa

**Machine** supplied with

• 1 x Main Filter • 1 x Pre-filter • 1 or 2 x Connection Kit • 1 x Power Cable • 1 x Manual

## **FUMECUBE LITE**

# **Options**

Compact, soldering fume extraction unit

Code

**Main filter** 

Description

110504 Chemical

**Pre-filter** 

200095 F6 Pad 200045

F8 / F9 Pad

#### Connection kits

#### 100294

#### Includes

1 x 2m x 50mm flexible hose 2 x connecting cuffs

1 x 95mm conical cowl

1 x 38mm pen nib

1 x clamped bench bracket



### Replacement **Arms**

Code

120128

120129

120199

Description

38mm x 1.5m flexible stainless steel arm

38mm x 0.75m flexible stainless steel arm

38mm x 0.5m flexible stainless steel arm

### **Interfacing**

Interfacing can remotely start the Purex machine when the connected machine starts.

Interfacing can also warn the connected machine when the Purex machine is in alarm.

Machine

10011010

10011010

Extractor

Take a look through our Interfacing Guide to see our extensive range of options

